



| I <sub>RMS</sub> | PF     | I <sub>THD</sub> (%) | Load | Fraction | Input  | DC Terminal Voltage (V)/ DC Load Current (A) |          |         |         |         | Output | Efficiency |
|------------------|--------|----------------------|------|----------|--------|--|----------|---------|---------|---------|--------|------------|
| Α                |        |                      | (%)  | of Load  | Watts  | 12V (cumulative of 12V1, 12V2, etc.)         | -12V     | 3.3V    | 5V*     | 5VSB    | Watts  | %          |
| 0.71             | 0.9801 | 15.46%               | 20%  | Light    | 80.11  | 12.1/4.3                                     | 11.9/0.1 | 3.4/1.6 | 5.2/1.9 | 5/0.5   | 70.82  | 88.41%     |
| 1.72             | 0.9835 | 10.11%               | 50%  | Typical  | 195.10 | 12/10.8                                      | 11.6/0.2 | 3.4/4   | 5.1/4.8 | 4.9/1.1 | 176.41 | 90.42%     |
| 3.47             | 0.9954 | 5.10%                | 100% | Full     | 398.20 | 12/21.7                                      | 11.4/0.4 | 3.4/8   | 5.1/9.6 | 4.9/2.2 | 350.96 | 88.14%     |







These tests were conducted by a third party independent testing firm on behalf of the 80 PLUS® Program. 80 PLUS is a certification program to promote highly-efficient power supplies (greater than 80% efficiency in the active mode) in technology applications. *http://www.80plus.org/* 

